

PMC-K4/EN

Extension Keypad

General

The extension Keypad is designed for the Remote Call Station PMC-8000/EN to increase its number of physical keys. It can efficiency of manual operation during help users to improve the emergency situation.

The keys of PMC-K4/EN can be configured to trigger emergency broadcast task. Each Remote Call Station can connect up to 8 units of PMC-K4/EN and each PMC-K4/EN has keys and 4 indicator LEDs.

Features

- Power supply from PMC-8000/EN.
- Four configurable keys with transparent covers to prevent accidental touches.
- Emergency indicator for each key.
- Flexible label slot with changeable labels.
- Each PMC-8000/EN can connect up to 8 extension keypads.
- Complies with EN54-16 standards.

Functions

The main function of the keys on PMC-K4/EN is to trigger the emergency broadcast task. The audio source of the task can be defined in the config software. The operation mode of the keys can be configured as press or toggle. The LED indicator shows the broadcast status of the task.

Technical Specifications

Power consumption: 0.5W

Power Supply Voltage: DC 5V

No. of Indicators: 4 red-color LEDs

No. of Keys: 4 configurable keys

Connections: Serial data and power connection via hidden flat cable



Operating Temperature: -10°C ~ +55°C

Storage Temperature: -40 °C ~ +70°C

Humidity: 95%, without condensation

Dimension (W×H×D): 100mm × 46.5mm × 200mm

Packing Dimension (W×H×D): 403mm × 133mm × 268mm

Net weight: 0.57 Kg

Gross weight: 1.2 Kg

Ordering Information

PMC-K4/EN: Extension Keypad